



Code No. : 5091/M

FACULTY OF ENGINEERING
B.E. 3/4 (E & EE/Inst.) II Semester (Main) Examination, May/June 2012
DIGITAL SIGNAL PROCESSING

Time : 3 Hours]

[Max. Marks : 75

Note : Answer *all* questions from Part A, Answer *any five* questions from Part B.

PART – A

(25 Marks)

1. $x(t) = 5 \cos 200 \pi t + 3 \sin 6000 \pi t + 2 \cos 12000 \pi t$. Determine the sampling frequency of the above signal. 2
2. Compute the convolution of the following signals : 3
 $x(n) = \{1, 2, 3, 4\}$, $h(n) = \{1, 1, 1\}$.
3. What are the two properties of twiddle factor which reduces the number of multiplications and addition in FFT ? 2
4. What is the difference between DTFT and DFT ? 3
5. Find the Z transform and ROC of the following signal ? 3
 $x(n) = -b^n u(-n - 1)$
6. Define one sided z-transform. 2
7. Write the expression for the order of the filter for Chebyshev filter. 2
8. Find the digital filter $H(z)$ from given analog filter below using impulse invariant method. 3
 $H(s) = \frac{1}{s(s+1)}$
9. What is the advantage of very large instruction word architecture in digital signal processor ? 3
10. What is the necessary condition for FIR filter to have a linear phase ? 2



PART – B

(5×10=50 Marks)

11. A system has the unit sample response $h(n) = \frac{1}{2} [\delta(n) + \delta(n-2)]$, determine and sketch the frequency response of the system. 10
12. Obtain radix – 2 DITFFT algorithm and find DFT of the following signal
 $x(n) = \{1, 2, 3, 4, 4, 3, 2, 1\}$ 10
13. a) Write symmetry properties of DFT. 5
b) Define energy signal and power signal. Determine whether unit step and unit ramp are energy signals or power signals? 5
14. a) Determine the impulse response of the following system using z-transform method. 5
 $y(n) - 2y(n-1) + y(n-2) = x(n) + x(n-1)$
b) Write the properties of z-transform. 5
15. Design a butterworth low pass filter for the specifications given below. 10
i) – 3db cut off frequency of 100 rad/sec
ii) – 25 db cutoff frequency of 250 rad/sec.
16. a) Write design procedure of FIR filter. 5
b) Explain the CALU, ARAU of TMS 320 c5x architecture. 5
17. Write short notes on :
a) Bilinear Transformation 5
b) Sampling, quantizing and coding. 5